

# 2 Circuits

## Keying codes

REV	DESCRIPTION	DATE
A36	ECN201805180001	2018.05.18

Code	P	K	V	CONFIGURATION
K01	1b 2a	1c 2d	1/2 --	
K02	1a 2b	1c --	1/2 --	
K03	2a --	1c 2d	1/2 --	
K05	1a 2b	2d --	1/2 --	
K07	1b 2ab	2d --	1/2 --	
K09	1b 2b	1c --	1/2 --	
K10	1a 2a	1c --	1/2 --	
K12	1a --	1c 2d	1/2 --	
K13	1ab --	2d --	1/2 --	
K14	1b 2a	1c --	1/2 --	
K15	2b --	1c 2d	1/2 --	
K48	1a 2b	1c 2d	1/2 --	

Code	P	K	V	CONFIGURATION
K78	1b 2ab	1c 2d	1/2 --	
K86	1ab 2a	1d 2c	-- --	
K99	-- --	-- --	1/2 --	
KA1	1b --	2d --	1/2 --	
KA2	1b --	1c 2d	1/2 --	
KA3	1ab --	1c --	1/2 --	
KA4	1a 2b	-- --	1/2 --	
KA5	1ab 2b	2d --	1/2 --	



Customer Drawing



TOLERANCE		Young Yak Enterprise Co., Ltd.			
X.	--	TITLE Keying Codes			
X.X	--				
X.XX	--				
X.XXX	--				
ANGULAR	--				
APPROVALS					
DRAWN	YunTing 18-MAY-2018	VIEW	SCALE	PART NO.	REV.
CHECKED	Nancy 18-MAY-2018		F	A504x	A36
APPROVED	Scott 18-MAY-2018	UNIT	SIZE	DWG NO.	SHEET
		MM	A4	A504x-Keying Codes	1 OF 22

## 2 Circuits

### Keying codes

Code	P	K	V	CONFIGURATION
KA6	2b --	-- --	1/2 --	
KA7	2a --	1c --	1/2 --	
KA8	2b --	2d --	1/2 --	
KA9	2ab --	1c --	1/2 --	
KB1	1ab 2b	1c --	1/2 --	
KB2	1a 2ab	1c 2d	1/2 --	
KB3	1ab --	1c 2d	1/2 --	
KB4	1ab 2a	1c --	1/2 --	
KB5	1b 2b	2d --	1/2 --	
KB6	1a 2ab	1c --	1/2 --	
KB7	1ab 2b	1c 2d	1/2 --	
KB8	1ab 2b	-- --	1/2 --	

Code	P	K	V	CONFIGURATION
KB9	2ab --	2d --	-- --	
KC1	1b 2b	2d --	-- --	
KC2	1b 2a	2d --	-- --	
KC3	1a 2b	-- --	-- --	
KC4	1ab 2ab	-- --	-- --	
KC5	2b --	1c --	1/2 --	
KC6	1a 2a	2d --	-- --	
KC7	1b 2a	2d --	1/2 --	

TOLERANCE		 Young Yak Enterprise Co., Ltd.			
X.	--	TITLE Keying Codes			
X.X	--				
X.XX	--				
X.XXX	--				
ANGULAR	--				
APPROVALS					
DRAWN	YunTing 18-MAY-2018	VIEW	SCALE	PART NO.	REV.
CHECKED	Nancy 18-MAY-2018		F	A504x	A36
APPROVED	Scott 18-MAY-2018	UNIT	SIZE	DWG NO.	SHEET
		MM	A4	A504x-Keying Codes	2 OF 22





Customer Drawing

## 2 Circuits

### Keying codes

Code	P	K	V	CONFIGURATION
KC8	1b 2a	-- --	-- --	
KC9	1a 2a	1c 2d	1/2 --	
KD1	2ab --	2d --	1/2 --	
KD2	1a 2a	2d --	1/2 --	
KD3	1b 2ab	-- --	1/2 --	
KD4	1b 2ab	2d --	-- --	
KD5	1b --	1cd --	-- --	
KD6	1b --	1c 2c	-- --	
KD7	1a 2b	2c --	-- --	
KD8	1ab 2a	2d --	1/2 --	
KD9	2b --	-- --	-- --	
KE1	-- --	1c 2d	1/2 --	

Code	P	K	V	CONFIGURATION
KE2	1a --	1c --	1/2 --	
KE3	-- --	2d --	1/2 --	
KE4	-- --	-- --	-- --	
KE5	1b 2b	1c --	-- --	
KE6	2a --	1c --	-- --	
KE7	1a 2ab	-- --	1/2 --	
KE8	1ab 2a	1c 2d	1/2 --	
KE9	1a --	2d --	1/2 --	

TOLERANCE		Young Yak Enterprise Co., Ltd.			
X.	--	 TITLE Keying Codes			
X.X	--				
X.XX	--				
X.XXX	--				
ANGULAR	--				
APPROVALS		APPROVALS			
DRAWN	YunTing 18-MAY-2018	VIEW	SCALE	PART NO.	REV.
CHECKED	Nancy 18-MAY-2018		F	A504x	A36
APPROVED	Scott 18-MAY-2018	UNIT	SIZE	DWG NO.	SHEET
		MM	A4	A504x-Keying Codes	3 OF 22



Customer Drawing

## 2 Circuits

### Keying codes

Code	P	K	V	CONFIGURATION
KF1	2b --	1c 2d	-- --	
KF2	1a --	-- --	1/2 --	
KF3	1ab 2b	-- --	-- --	
KF4	2a --	2d --	1/2 --	
KF5	2ab --	-- --	1/2 --	
KF6	2b --	1c --	-- --	
KF7	1ab 2a	1c --	-- --	
KF8	1ab --	-- --	1/2 --	
KF9	1b 2b	-- --	1/2 --	
KG1	1b --	-- --	1/2 --	
KG2	-- --	2d --	-- --	
KG3	1b --	1c 2d	-- --	

Code	P	K	V	CONFIGURATION
KG4	-- --	1c --	1/2 --	
KG5	1ab 2ab	1c 2d	1/2 --	
KG6	1ab 2ab	1cd 2cd	-- --	
KG7	1ab --	2c --	-- --	
KG8	2a --	-- --	1/2 --	
KG9	1ab --	1c --	-- --	
KH1	-- --	1c 2d	-- --	
KH2	1b --	-- --	-- --	


















Customer Drawing

TOLERANCE		Young Yak Enterprise Co., Ltd.			
X.	--	 TITLE Keying Codes			
X.X	--				
X.XX	--				
X.XXX	--				
ANGULAR	--				
APPROVALS		REV.			
DRAWN	YunTing 18-MAY-2018	VIEW	SCALE	PART NO.	A36
CHECKED	Nancy 18-MAY-2018		F	A504x	
APPROVED	Scott 18-MAY-2018	UNIT	SIZE	DWG NO.	SHEET
		MM	A4	A504x-Keying Codes	4 OF 22

## 2 Circuits



### Keying codes

Code	P	K	V	CONFIGURATION
KH3	1ab --	2d --	-- --	
KH4	1b --	1c --	-- --	
KH5	2a --	2d --	-- --	
KH6	2ab --	1c --	-- --	
KH7	1a 2b	1c 2d	-- --	
KH8	1ab 2b	1c --	-- --	
KH9	1ab --	1c 2d	-- --	
KJ1	1ab 2b	2d --	-- --	
KJ2	1ab 2b	1c 2d	-- --	
KJ3	1ab 2a	2d --	-- --	
KJ4	1a --	1c --	-- --	
KJ5	1ab 2a	1c 2d	-- --	

Code	P	K	V	CONFIGURATION
KJ6	2a --	-- --	-- --	
KJ7	1a 2b	1d 2c	-- --	
KJ8	1ab 2a	-- --	1/2 --	
--	--	--	--	



Customer Drawing

TOLERANCE		Young Yak Enterprise Co., Ltd.			
X.	--	 TITLE Keying Codes			
X.X	--				
X.XX	--				
X.XXX	--				
ANGULAR	--				
APPROVALS					
DRAWN	YunTing 18-MAY-2018	VIEW	SCALE	PART NO.	REV.
CHECKED	Nancy 18-MAY-2018		F	A504x	A36
APPROVED	Scott 18-MAY-2018	UNIT	SIZE	DWG NO.	SHEET
		MM	A4	A504x-Keying Codes	5 OF 22

# 3 Circuits

## Keying codes

Code	P	K	V	CONFIGURATION
K01	1b --	1c 2d	1/2 --	
K02	2b 3b	1d 2c	2/3 --	
K03	1b 3a	1c --	1/2 --	
K04	1a --	3c --	1/2 --	
K05	1ab --	3d --	1/2 --	
K06	1a 3b	1c --	1/2 --	
K08	2b --	2d --	1/2 --	
K10	3b --	1c 3d	2/3 --	
K32	1b 2a 3b --	1c 2d	1/2 --	
K37	3b --	1c 3d	1/2 --	
K44	2a --	1d 3d	2/3 --	
K53	1ab --	2d --	1/2 --	
K67	2b 3b	-- --	1/2 --	

Code	P	K	V	CONFIGURATION
K98	1a 3a	3c --	1/2 --	
K119	1b 2b	1c 2d	1/2 --	
K124	1b 2ab 3b --	-- --	2/3 --	
K130	2b 3ab	1c 2d 3cd --	1/2 --	
KA1	2a --	3d --	2/3 --	
KA2	-- --	1c 2d 3d	1/2 --	
KA3	1b --	2d --	1/2 --	
KA4	1b --	1c --	1/2 --	
KA5	2a 2b	1c 3d	1/2 --	



Customer Drawing

TOLERANCE		Young Yak Enterprise Co., Ltd.			
X.	--	<div style="text-align: center;"> <b>Young Yak Enterprise Co., Ltd.</b> </div> <div style="text-align: center; margin-top: 10px;"> <b>TITLE</b>                      Keying Codes                 </div>			
X.X	--				
X.XX	--				
X.XXX	--				
ANGULAR	--				
APPROVALS		APPROVALS			
DRAWN	YunTing 18-MAY-2018	VIEW	SCALE	PART NO.	REV.
CHECKED	Nancy 18-MAY-2018		F	A504x	A36
APPROVED	Scott 18-MAY-2018	UNIT	SIZE	DWG NO.	SHEET
		MM	A4	A504x-Keying Codes	6 OF 22

### 3 Circuits Keying codes

Code	P	K	V	CONFIGURATION
KA6	2a --	2d 3c	1/2 --	
KA7	2b 3b	1c 1d 2c 3d	2/3 --	
KA8	2a 3b	1d 2c	-- --	
KA9	1a 3b	1d 2c	-- --	
KB1	2b 3b	1d --	2/3 --	
KB2	1a 3a	1c --	1/2 --	
KB3	1b --	2d 3c	1/2 --	
KB4	3b --	1d 3d	2/3 --	
KB5	-- --	1c 3d	1/2 --	
KB6	1b 2a	1c 2d	1/2 --	
KB7	2a --	1d --	2/3 --	
KB8	3b --	1c 3d	-- --	
KB9	2b 3a	1c 2d	1/2 --	

Code	P	K	V	CONFIGURATION
KC1	2a 3a	1c 3d	1/2 --	
KC2	-- --	-- --	1/2 2/3	
KC3	1a 2b 3a --	1d 2c	2/3 --	
KC4	2d 3ab	1d 2c 3d --	2/3 --	
KC5	2a --	1d 2c 3d --	2/3 --	
KC6	2a 3b	-- --	1/2 --	
KC7	1a 3b	-- --	1/2 --	
KC8	1b 2ab 3a --	1c 2d	1/2 --	
KC9	-- --	1c --	2/3 --	



Customer Drawing

TOLERANCE		 Young Yak Enterprise Co., Ltd. TITLE Keying Codes			
X.	--				
X.X	--				
X.XX	--				
X.XXX	--				
ANGULAR	--	APPROVALS			
DRAWN	YunTing 18-MAY-2018	VIEW	SCALE	PART NO.	REV.
CHECKED	Nancy 18-MAY-2018		F	A504x	A36
APPROVED	Scott 18-MAY-2018	UNIT	SIZE	DWG NO.	SHEET
		MM	A4	A504x-Keying Codes	7 OF 22

# 3 Circuits

## Keying codes

Code	P	K	V	CONFIGURATION
KD1	1a 2a	1c 2d	1/2 --	
KD2	1a 2b	1c 3d	1/2 --	
KD3	1b 3b	1c 3c	1/2 --	
KD4	1a 3a	2d --	1/2 --	
KD5	1b 2b 3b --	1c 3c	1/2 --	
KD6	1a 3b	1c 2d 3d --	1/2 --	
KD7	1a 3b	1c 3d	1/2 --	
KD8	1a 3b	1c 3cd	1/2 --	
KD9	2b 3b	1cd 3d	2/3 --	
KE1	2b 3b	1c 3d	2/3 --	
KE2	2b 3b	1c 2c 3d --	2/3 --	
KE3	1a --	-- --	-- --	
KE4	1b 2a 3b --	1c 2d 3d --	1/2 --	

Code	P	K	V	CONFIGURATION
KE5	2a --	1d 3d	2/3 --	
KE6	1ab 2ab 3ab --	-- --	-- --	
KE7	2a 3b	-- --	2/3 --	
KE8	2b 3b	-- --	2/3 --	
KE9	1ab --	-- --	2/3 --	
KF1	2a 3b	-- --	-- --	
KF2	2b 3b	-- --	-- --	
KF3	1ab --	-- --	-- --	
KF4	1ab 2a 3ab --	1c --	1/2 --	



Customer Drawing

TOLERANCE		 Young Yak Enterprise Co., Ltd. TITLE Keying Codes			
X.	--				
X.X	--				
X.XX	--				
X.XXX	--				
ANGULAR	--	APPROVALS			
DRAWN	YunTing 18-MAY-2018	VIEW	SCALE	PART NO.	REV.
CHECKED	Nancy 18-MAY-2018		F	A504x	A36
APPROVED	Scott 18-MAY-2018	UNIT	SIZE	DWG NO.	SHEET
		MM	A4	A504x-Keying Codes	8 OF 22



### 3 Circuits Keying codes

Code	P	K	V	CONFIGURATION
KF5	2b 3a	1d 2c 3d ---	2/3 ---	
KF6	1b 2ab	3cd ---	1/2 ---	
KF7	1a 3b	3d ---	1/2 ---	
KF8	2a 3a	3d ---	1/2 ---	
KF9	2a ---	2c 3d	2/3 ---	
KG1	2b 3ab	3d ---	1/2 ---	
KG2	--- ---	2d ---	1/2 ---	
KG3	1b ---	1c 2d 3c ---	--- ---	
KG4	1a 2b 3b ---	1cd 3d	2/3 ---	
KG5	1ab 2ab 3ab ---	1c 2d 3cd ---	1/2 ---	
KG6	1ab 2ab 3ab ---	1cd 2c 3d ---	2/3 ---	
KG7	1ab 2ab 3ab ---	1cd 2cd 3cd ---	--- ---	

Code	P	K	V	CONFIGURATION
KG8	3b ---	1d 2c	2/3 ---	
KG9	--- ---	1d 3d	2/3 ---	
KH1	3b ---	1c 3c	1/2 ---	
KH2	1a 3a	3d ---	1/2 ---	
KH3	1a ---	1c 2d 3c ---	1/2 ---	
KH4	1a 3b	1d ---	2/3 ---	
KH5	1a 2ab	1cd 3d	2/3 ---	



Customer Drawing

TOLERANCE		 Young Yak Enterprise Co., Ltd.					
X.	---					TITLE	
X.X	---						
X.XX	---						
X.XXX	---						
ANGULAR	---						
APPROVALS		Keying Codes					
DRAWN	YunTing 18-MAY-2018	VIEW	SCALE	PART NO.	REV.		
CHECKED	Nancy 18-MAY-2018		F	A504x	A36		
APPROVED	Scott 18-MAY-2018	UNIT	SIZE	DWG NO.	SHEET		
		MM	A4	A504x-Keying Codes	9 OF 22		

# 4 Circuits



## Keying codes

Code	P	K	V	CONFIGURATION
K01	1b --	3c 4d	1/2 3/4	
K02	1a 4b	1c --	1/2 3/4	
K03	1a 4b	4d --	1/2 3/4	
K04	3b --	3d --	2/3 --	
K07	2a 4b	2d --	1/2 3/4	
K17	1ab 3ab 4a --	1c --	1/2 3/4	
K19	1b 2b 3a 4ab	1cd 3d 4d --	2/3 --	
K29	1b 2a 3ab 4b	1c 2d 3c --	1/2 3/4	
K31	1a 2b 3b --	4d --	1/2 3/4	
K37	1b 2a 3a 4b	1c 4d	1/2 3/4	
K63	1b 2ab 3b 4b	2d 3c	1/2 3/4	
K65	1a 2b 3b 4a	1c 3c 4d --	1/2 3/4	

Code	P	K	V	CONFIGURATION
K79	1b 2a 3a 4b	1c 2d 3c --	1/2 3/4	
K86	1a 2b 3b 4a	2d 3c 4d --	1/2 3/4	
K100	2ab 3a 4a --	1c 3c	1/2 3/4	
K102	1b --	1c 2d 3c 4d	1/2 3/4	
K109	1b 2a 3a 4b	2d 4d	1/2 3/4	
K110	1a 2b 4a --	1c 4d	1/2 3/4	
K120	1b 2b 3b 4a	1c 3c 4d --	1/2 3/4	
K142	1b 2a 3b 4a	1c 2d 3c 4d	1/2 3/4	
KA1	2a 2b 3b 4b	1c 2d 3c 4d	1/2 3/4	



Customer Drawing

TOLERANCE		 Young Yak Enterprise Co., Ltd. TITLE Keying Codes			
X.	--				
X.X	--				
X.XX	--				
X.XXX	--				
ANGULAR	--	APPROVALS			
DRAWN	YunTing 18-MAY-2018	VIEW	SCALE	PART NO.	REV.
CHECKED	Nancy 18-MAY-2018		F	A504x	A36
APPROVED	Scott 18-MAY-2018	UNIT	SIZE	DWG NO.	SHEET
		MM	A4	A504x-Keying Codes	10 OF 22

# 4 Circuits Keying codes

Code	P	K	V	CONFIGURATION
KA2	3b 4ab	1c 3d 4cd ---	1/2 --	
KA3	1b --	3c --	1/2 --	
KA4	1a 4b	1c 4cd	2/3 --	
KA5	1a 2a 3ab --	1c 3c	1/2 3/4	
KA6	3a --	3c --	1/2 3/4	
KA7	1b 2a 4b --	1c 2d 3c 4d	1/2 3/4	
KA8	2a 3ab 4b --	1c 2d 3c 4d	1/2 3/4	
KA9	-- --	3c 4d	1/2 3/4	
KB1	3ab 4b	1c --	1/2 3/4	
KB2	3a --	1c 2d -- 4d	1/2 3/4	
KB3	1ab 4a	2c --	2/3 --	
KB4	1b 3b	2c 4d	2/3 --	

Code	P	K	V	CONFIGURATION
KB5	1b 4a	2c 3d 4d --	2/3 --	
KB6	1a 4b	4d --	1/2 3/4	

35



Customer Drawing

TOLERANCE		 Young Yak Enterprise Co., Ltd. TITLE Keying Codes			
X.	--				
X.X	--				
X.XX	--				
X.XXX	--				
ANGULAR	--	APPROVALS			
DRAWN	YunTing 18-MAY-2018	VIEW	SCALE	PART NO.	REV.
CHECKED	Nancy 18-MAY-2018		F	A504x	A36
APPROVED	Scott 18-MAY-2018	UNIT	SIZE	DWG NO.	SHEET
		MM	A4	A504x-Keying Codes	11 OF 22

# 5 Circuits

## Keying codes

Code	P	K	V	CONFIGURATION
K01	1a 5b	1c 3d	1/2 2/3	
K02	2b --	2d --	1/2 4/5	
K04	1a 4a	3d --	1/2 4/5	
K12	1ab 4b 5ab --	1c 4c 5d --	1/2 4/5	
K28	1a 2a 4b 5ab	1c 4c 5d --	1/2 4/5	
K30	1a 3a	1c 3d	1/2 4/5	
K31	1a 5b	1c 2d 3c 5d	1/2 3/4	
K43	2a --	1c 5d	2/3 4/5	
K44	2a 4b	1c 2d 4d --	1/2 3/4	
K45	4b 5a	1c 3d 4c 5d	1/2 4/5	
K50	1a 5b	3d 4c	2/3 --	
K51	1b 2a 4a --	1c 4c 5d --	1/2 4/5	

Code	P	K	V	CONFIGURATION
K64	1ab 4a 5d --	3d 4c 5d --	1/2 4/5	
K69	2ab 4a 5b --	1c 2d 4c --	1/2 4/5	
K73	1a 3a 4b 5a	3c 4c	1/2 4/5	
K86	1a 5b	1c 2d 3c 5d	1/2 4/5	
KA1	2b 4b	2c 5d	2/3 4/5	
KA2	2b --	2d 5d	1/2 3/4	
KA3	3a 4b	3c --	1/2 4/5	
KA4	3a 3b	5d --	1/2 3/4	
KA5	5b --	3c 5d	3/4	












Customer Drawing

TOLERANCE		 Young Yak Enterprise Co., Ltd.			
X.	--				
X.X	--				
X.XX	--				
X.XXX	--				
ANGULAR --		TITLE			
APPROVALS		Keying Codes			
DRAWN	YunTing 18-MAY-2018	VIEW	SCALE	PART NO.	REV.
CHECKED	Nancy 18-MAY-2018		F	A504x	A36
APPROVED	Scott 18-MAY-2018	UNIT	SIZE	DWG NO.	SHEET
		MM	A4	A504x-Keying Codes	12 OF 22

# 5 Circuits



## Keying codes

Code	P	K	V	CONFIGURATION
KA6	1a 2b 3a --	3c 5d	1/2 4/5	
KA7	1a 2b 3b 5b	1c 2d 3c 4d 5cd --	1/2 3/4	
KA8	1a 5b	1c 3d	-- --	
KA9	1a 5b	1c --	1/2 3/4	
KB1	1b 2b 4a --	1c 5d	1/2 4/5	
KB2	2b --	1c 2d 3c 4c 5d --	1/2 4/5	
KB3	5b --	3d --	1/2 --	
KB4	3b --	3d --	1/2 4/5	
KB5	4b 5a	2c 4d 5cd --	2/3 --	
--	-- --	-- --	-- --	
--	-- --	-- --	-- --	
--	-- --	-- --	-- --	

Code	P	K	V	CONFIGURATION



Customer Drawing

TOLERANCE		 Young Yak Enterprise Co., Ltd. TITLE Keying Codes			
X.	--				
X.X	--				
X.XX	--				
X.XXX	--				
ANGULAR	--	APPROVALS			
DRAWN	YunTing 18-MAY-2018	VIEW	SCALE	PART NO.	REV.
CHECKED	Nancy 18-MAY-2018		F	A504x	A36
APPROVED	Scott 18-MAY-2018	UNIT	SIZE	DWG NO.	SHEET
		MM	A4	A504x-Keying Codes	13 OF 22

# 6 Circuits

## Keying codes

Code	P	K	V	CONFIGURATION
K00	1ab 2ab 3ab 4ab 5ab 6ab	1c 2d 3cd 4c 5d 6cd	1/2 4/5	
K01	1b --	3c 6d	1/2 4/5	
K06	1a 2b 4a 5ab 6b --	1c 3c 4d 6d	1/2 3/4 5/6 --	
K15	1b 2a 3a 4b 5ab 6b	1c 6d	2/3 5/6	
K21	1ab 2ab 3ab 6a	1cd 2c 3d 5d 6c --	4/5 --	
K29	1b 2ab 3a 6ab	2d 4c 6d --	1/2 5/6	
K30	1a 3b 4b --	1c 5d 6c --	1/2 4/5	
K35	1a 2b 6b --	3c 4d 6d --	1/2 5/6	
K50	1b 2a 3b --	1c 2d 5c 6d	1/2 3/4 5/6 --	
K51	1b 2b 3b --	1c 5c 6d --	1/2 3/4 5/6 --	
K66	1b 2a 3a 4b 5b 6ab	1c 2d 3c 6d	1/2 3/4 5/6 --	
K73	1a 2b 4a 6b	2d 3c 6cd --	1/2 3/4	

Code	P	K	V	CONFIGURATION
K99	-- --	-- --	-- --	
KA1	1b 5b	1c 6d	2/3 5/6	
KA2	1b --	3c --	1/2 5/6	
KA3	1b --	4c --	1/2 5/6	
KA4	1b 2a 3a 4b 5a 6b	1c 2d 4d 6d	1/2 3/4 5/6 --	
KA5	1ab 2b 3a 6b	2d 3c	1/2 5/6	
KA6	1a 2b 4a 6b	1c 6cd	1/2 3/4	
KA7	1b 2ab 3b 4ab 5a 6b	2d 4d 6d --	1/2 3/4 5/6 --	
KA8	1ab 4ab	3d 6d	1/2 4/5	



Customer Drawing

TOLERANCE		 Young Yak Enterprise Co., Ltd.			
X.	--				
X.X	--				
X.XX	--				
X.XXX	--				
ANGULAR --		TITLE			
APPROVALS		Keying Codes			
DRAWN	YunTing	VIEW	SCALE	PART NO.	REV.
	18-MAY-2018		F	A504x	A36
CHECKED	Nancy	UNIT	SIZE	DWG NO.	SHEET
	18-MAY-2018	MM	A4	A504x-Keying Codes	14 OF 22
APPROVED	Scott				
	18-MAY-2018				

# 6 Circuits

## Keying codes

Code	P	K	V	CONFIGURATION
KA9	1b 3a	3c 6d	1/2 4/5	
KB1	1a 2b 3ab 5b 6b --	1c 4d 6d --	1/2 3/4 5/6 --	
KB2	3b 5b	2d --	-- --	
KB3	1a 3b 4b 6a	1c 4c	1/2 4/5	
KB4	1a 6a	3c 5c 6d --	1/2 5/6	
KB5	5b --	1cd 2cd 3d 4d 5c 6d	5/6 --	
KB6	2b 6b	4d --	-- --	
KB7	1b --	3c --	-- --	
KB8	1a --	3d 6d	1/2 5/6	
KB9	2a 3b 5a 6b	1c 2d 4c 5d	1/2 4/5	
KC1	1a --	3c 6d	-- --	
KC2	5b 6a	3c 5c 6d --	5/6 --	

Code	P	K	V	CONFIGURATION
KC3	1ab 2b 3b --	2d 5c 6d --	-- --	
KC4	1a 3b 4ab --	1c 6d	1/2 4/5	
KC5	1b 3a 4a 6a	1c 4c	1/2 4/5	
KC6	3a 6b	1c 6d	1/2 5/6	
KC7	3a 4a	1c 3c 5c --	1/2 5/6	
KC8	2a 3b 5b --	3c --	1/2 3/4 5/6 --	
KC9	1b 3ab 4a 5ab 6b --	1c 2d 4d 6d	1/2 3/4 5/6 --	
KD1	5b 6ab	3c 5d 6cd --	3/4 --	
KD2	1b 2ab 3ab 6a	1cd 2c 3d 5d 6cd --	4/5 --	

TOLERANCE	
X.	--
X.X	--
X.XX	--
X.XXX	--
ANGULAR	--
APPROVALS	
DRAWN	YunTing 18-MAY-2018
CHECKED	Nancy 18-MAY-2018
APPROVED	Scott 18-MAY-2018



Young Yak Enterprise Co., Ltd.

TITLE

Keying Codes



Customer Drawing

VIEW	SCALE	PART NO.	REV.
	F	A504x	A36
UNIT	SIZE	DWG NO.	SHEET
MM	A4	A504x-Keying Codes	15 OF 22

# 6 Circuits Keying codes

Code	P	K	V	CONFIGURATION
KD3	1ab 2b 3b --	2d 5c 6d --	1/2 3/4 5/6 --	
KD4	5b 6a -- --	3c 5d 6cd --	3/4 -- -- --	

Code	P	K	V	CONFIGURATION



Customer Drawing

<b>TOLERANCE</b>		Young Yak Enterprise Co., Ltd.			
X.	--	TITLE			
X.X	--	Keying Codes			
X.XX	--				
X.XXX	--				
ANGULAR --					
<b>APPROVALS</b>					
DRAWN	YunTing 18-MAY-2018	VIEW	SCALE	PART NO.	REV.
CHECKED	Nancy 18-MAY-2018		F	A504x	A36
APPROVED	Scott 18-MAY-2018	UNIT	SIZE	DWG NO.	SHEET
		MM	A4	A504x-Keying Codes	16 OF 22



# 7 Circuits

## Keying codes

Code	P	K	V	CONFIGURATION
K01	-- --	3c 4d 7c --	1/2 5/6	
K19	1b 2ab 4a 5b 6a 7b	1c 2d 4c 5d 6c 7d	1/2 4/5 6/7 --	
K22	1ab 2ab 3ab 4ab 5ab 6ab 7ab -- --	3c 4d 7c --	1/2 5/6	
K23	2a 4b	1c 2d 4d 7d	1/2 3/4 5/6 --	
K30	3a 4a	3d 7d	1/2 5/6	
K35	2b --	2d 7c	1/2 3/4 5/6 --	
K41	2a --	1c 5d	2/3 4/5	
K48	1b 7a	2c 5d	2/3 6/7	
K59	1ab 2b 3a 4b 6a --	1d 3d 4cd 5d 7d --	2/3 6/7	
K63	1a 3a 7b --	2d 5d 6c --	1/2 3/4 6/7 --	
K76	1b 4a 7b --	1c 2d 3c 4d 7cd --	1/2 5/6	
KA2	6b --	4c --	1/2 5/6	

Code	P	K	V	CONFIGURATION
KA3	-- --	2d 3c 7d --	1/2 5/6	
KA4	1b 2a 3a 6a	1c 2d	1/2 5/6	
KA5	1a 7a	4d 7d	1/2 3/4 5/6 --	
KA6	4b 6b	3d --	-- --	
KA7	-- --	2c 7d	4/5 --	
KA8	1b 3b 5ab --	2d 7cd	1/2 5/6	
KA9	1a 2b 4b 5b	3c 4d 5c 6d	1/2 3/4 5/6 --	
KB1	1b 3b 5ab --	2d 3c 7cd --	1/2 5/6	



Customer Drawing

TOLERANCE		 Young Yak Enterprise Co., Ltd. TITLE Keying Codes			
X.	--				
X.X	--				
X.XX	--				
X.XXX	--				
ANGULAR		--			
APPROVALS					
DRAWN	YunTing	VIEW	SCALE	PART NO.	REV.
	18-MAY-2018		F	A504x	A36
CHECKED	Nancy	UNIT	SIZE	DWG NO.	SHEET
	18-MAY-2018	MM	A4	A504x-Keying Codes	17 OF 22
APPROVED	Scott				
	18-MAY-2018				

# 7 Circuits

## Keying codes

Code	P	K	V	CONFIGURATION
KB2	2a 3b 4a 5ab 7ab --	2d 3c 5c 7c	1/2 3/4 5/6 --	
KB3	2a 3b 4b 5a 6b 7b	2d 5d 6c 7d	1/2 3/4 6/7 --	
KB4	4b --	1c 2d 4d --	1/2 6/7	
KB5	2a 3b 4b 6b 7b --	2d 5d 6c 7d	1/2 3/4 6/7 --	
KB6	1a 2b 3b 6b 7a --	1c 2d 3c 4d 6c 7d	1/2 3/4 6/7 --	
KB7	2a 4a 5ab 7b	2d 3c 5c 7c	1/2 3/4 5/6 --	
KB8	1a 5b 6ab 7b	1c 3d	2/3 6/7	
KB9	1a 6b	4c 7c	1/2 5/6	
KC1	1a 4a 5b 6b	4c 7c	1/2 5/6	
KC2	-- --	3d 7c	1/2 5/6	
KC3	-- --	4c 7c	1/2 5/6	
KC4	-- --	2d 3c 4d 5c 6d 7c	1/2 5/6	

Code	P	K	V	CONFIGURATION
KC5	1a 6b	3c 4d 7c --	1/2 5/6	
KC6	1a 5b 7b --	4d 6c 7d --	-- --	
KC7	1a 5b 7b --	4d 5d	-- --	
KC8	1ab 2b 3a 7b	1d 2cd 4d 5d 7d	3/4 6/7	
KC9	2b --	2d 7c	1/2 5/6	
KD1	-- --	4c --	1/2 5/6	
KD2	1a 6b	3c 7c	4/5 --	



Customer Drawing

TOLERANCE		 Young Yak Enterprise Co., Ltd. TITLE Keying Codes			
X.	--				
X.X	--				
X.XX	--				
X.XXX	--				
ANGULAR	--	APPROVALS			
DRAWN	YunTing 18-MAY-2018	VIEW	SCALE	PART NO.	REV.
CHECKED	Nancy 18-MAY-2018		F	A504x	A36
APPROVED	Scott 18-MAY-2018	UNIT	SIZE	DWG NO.	SHEET
		MM	A4	A504x-Keying Codes	18 OF 22

# 8 Circuits

## Keying codes

Code	P	K	V	CONFIGURATION
K32	1a 2a 4ab 5a 6b 8a	1c 3c 5c 7c 8d --	1/2 3/4 5/6 7/8	
K38	1ab 3b 5a 6b 7a 8b	1c 3c 4d 8d	1/2 3/4 5/6 7/8	
K42	1b 6b	3c 4d 6c 7d	1/2 3/4 6/7 --	
K44	1a 4b 5b 6a 8b --	4d 6d 7c 8d	1/2 3/4 5/6 7/8	
K49	8b --	2c 3d	2/3 --	
K57	1b 2b 7b --	1c 2d 4c 6d 7c --	1/2 5/6 7/8 --	
K58	1a 2ab 4ab 5b 7b 8b	4d 5c 6d 7c	1/2 3/4 5/6 7/8	
K60	4b 6b 7a --	1c 5c 8d --	1/2 3/4 5/6 7/8	
K62	-- --	4c 5d	1/2 7/8	
K63	-- --	3c 6d	1/2 7/8	
K77	1ab 3ab 5a 6b 7b 8a	1c 3c 5c 7c	1/2 3/4 5/6 7/8	
KA2	2b 6b	-- --	2/3 7/8	

Code	P	K	V	CONFIGURATION
KA3	2b 6b	2d 8c	1/2 6/7	
KA4	-- --	3d 4c 5d 6c 7d 8c	2/3 6/7	
KA5	-- --	2d 3c 6d 7c	1/2 7/8	
KA6	3a 7a	-- --	1/2 6/7	
KA7	-- --	1c 2d 5d 6c 7c --	1/2 4/5 7/8 --	
KA8	4b 7b 8b --	1cd 2c 3c 4c 5d 6c 7c 8d --	4/5 7/8	
KA9	1ab 2b 3b 4ab 6a 7a 8b -- --	2d 4d 5c 6d 8d --	1/2 7/8	
KB1	1b 2b 3a 8b	1c 3c 4d 7c 8d --	1/2 3/4 7/8 --	
KB2	1a 2b 3b 7b 8a --	1c 2d 3c 4d 5c 6d 7c 8d --	1/2 3/4 5/6 7/8	



Customer Drawing

TOLERANCE					
X.	--				
X.X	±0.25	TITLE			
X.XX	±0.15				
X.XXX	±0.05	Keying Codes			
ANGULAR	--				
APPROVALS		PART NO. A504x			
DRAWN	YunTing 18-MAY-2018	VIEW	SCALE	REV. A36	
CHECKED	Nancy 18-MAY-2018		F	DWG NO. A504x-Keying Codes	
APPROVED	Scott 18-MAY-2018	UNIT	SIZE	SHEET 19 OF 22	
		MM	A4		

# 9 Circuits

## Keying codes

Code	P	K	V	CONFIGURATION
K04	5b -- --	3d 7d --	1/2 6/7 --	
K30	1a 2ab 3ab 6a 7a 8b 9b -- --	2d 3c 4d 5d 9d --	1/2 3/4 6/7 7/8 8/9 --	
K33	2b 6ab 7a 8a 9b --	2d 6c 7d 9d -- --	1/2 4/5 6/7 8/9 -- --	
K35	1a 2b 3a 6a 8b --	2d 3c 4d 5d 7d 8c 9d -- --	1/2 3/4 6/7 8/9 -- --	
K42	2a 3b 7b	1c 2d 5c 6d 7c 8d	1/2 3/4 5/6 7/8 -- --	
K43	2b 3b 4a 5a 6b --	4c 8c 9d	1/2 4/5 6/7 8/9 -- --	
K48	1b 7a 8a 9b -- --	2c 5d 9d	2/3 6/7 8/9	
K49	2b 3b 4b 6a -- --	1c 2d 4d 5c 9d --	1/2 3/4 6/7 8/9 -- --	
K52	1a 3a 4ab 5ab 7a 8b 9b -- --	2d 4c 5d 6c 7d 9d	1/2 6/7 8/9	
K53	1a 2b 3b 4b 6a --	1c 3c 5c 9d -- --	1/2 3/4 6/7 8/9 -- --	
K57	1a 2b 4b 8b 9a --	1c 4d 8c	1/2 3/4 6/7 8/9 -- --	
K58	1b 2a 4b 5a 8b 9b	1c 2d 7d 8c -- --	1/2 4/5 6/7 8/9 -- --	

Code	P	K	V	CONFIGURATION
K59	1a 1b 2b 3a 7b 8a 9b -- --	1d 2cd 4d 5d 7d 9d	3/4 6/7 8/9	
--	-- --	-- --	-- --	
--	-- --	-- --	-- --	
--	-- --	-- --	-- --	
--	-- --	-- --	-- --	
--	-- --	-- --	-- --	
--	-- --	-- --	-- --	
--	-- --	-- --	-- --	
--	-- --	-- --	-- --	
--	-- --	-- --	-- --	



Customer Drawing

<b>TOLERANCE</b> X. -- X.X ±0.25 X.XX ±0.15 X.XXX ±0.05 ANGULAR --		<b>Young Yak Enterprise Co., Ltd.</b>		
<b>APPROVALS</b> DRAWN YunTing 18-MAY-2018 CHECKED Nancy 18-MAY-2018 APPROVED Scott 18-MAY-2018		<b>TITLE</b> Keying Codes		
VIEW	SCALE F	PART NO. A504x	REV. A36	
UNIT MM	SIZE A4	DWG NO. A504x-Keying Codes	SHEET 20 OF 22	

# 10 Circuits

## Keying codes

Code	P	K	V	CONFIGURATION
K36	1b 3b 5b 9a ---	1c 6d 7c 9c 10d --	1/2 3/4 5/6 7/8 9/10 --	
K46	2ab 3a 4a 5a 9a 10a	2d 4d 7cd 8c 10d --	1/2 3/4 5/6 8/9 -- --	
K50	1b 5a 8b 9a 10b --	3c 4d 8d 9c -- --	1/2 3/4 5/6 7/8 9/10 --	
K51	1b 3a 4ab 6b 9ab --	1c 5d 6c 7d 9c --	1/2 4/5 6/7 9/10 -- --	
K52	1b 4a 7a 9a ---	1c 2d 6c 8d 9c --	1/2 4/5 7/8 9/10 -- --	
K53	1b 2a 4a 6b 7b 8ab 10b -- --	1c 3c 4d 5c 6d 8d 9c -- --	1/2 3/4 5/6 7/8 9/10 --	
K54	1b 2b 3a 4b 5b 6a 7a 9a --	1c 4d 5c 6d 7c --	1/2 3/4 5/6 7/8 -- --	
K64	1b 2a 4b 6a 7b 8b 9a 10b --	1c 3c 4d 5c 6d 8d 9c -- --	1/2 3/4 5/6 7/8 9/10 --	
K70	2b 3b 4a 5ab 6b 8a 10b -- --	1d 2c 8d 9c -- --	2/3 5/6 7/8 9/10 -- --	
K71	1a 4a 6a 10b ---	2d 4d 8d 9c -- --	1/2 3/4 6/7 9/10 -- --	
K72	1a 4a 8a 10a ---	1c 6b 9c	1/2 3/4 5/6 7/8 9/10 --	
K74	2a 3b 6a 9a ---	3c 8d 9c	1/2 3/4 5/6 7/8 9/10 --	

Code	P	K	V	CONFIGURATION
K75	3a 4b 5b 6a 7a 9b 10b -- --	1c 3c 5c 7c 8d 9c	1/2 3/4 5/6 7/8 9/10 --	
K76	1ab 4ab 5a 6b 7ab 10b	1c 3c 6d 9d 10cd --	1/2 3/4 5/6 7/8 -- --	
K78	2ab 3a 4b 6a 7ab 8b 9b 10b --	1c 3c 5c 6d 8d 9c	1/2 3/4 5/6 7/8 9/10 --	
KA2	4b 6b 8ab	6c 10d	-- --	
KA3	2b 5a 10b	1d 3d 7d 10d -- --	-- --	
KA4	1a 3b 7b 9b -- --	1c 2d 4d 5c 7c --	1/2 3/4 5/6 7/8 9/10 --	



Customer Drawing

<b>TOLERANCE</b> X. -- X.X ±0.25 X.XX ±0.15 X.XXX ±0.05 ANGULAR --		<b>Young Yak Enterprise Co., Ltd.</b>		
<b>APPROVALS</b> DRAWN YunTing 18-MAY-2018 CHECKED Nancy 18-MAY-2018 APPROVED Scott 18-MAY-2018		<b>TITLE</b> Keying Codes		
VIEW SCALE F UNIT MM	PART NO. A504x DWG NO. A504x-Keying Codes	REV. A36 SHEET 21 OF 22		

# 11 Circuits

## Keying codes

Code	P	K	V	CONFIGURATION
K28	1b 2a 3a 6b 7b 10b 11a -- --	1c 2d 6d 7c 8d 10c 11d -- --	1/2 3/4 5/6 7/8 10/11 --	
K43	1b 11b --	3c 9d --	3/4 8/9 --	
K55	1b 2b 3a 4b 5b 11b	1c 3c 5c 9d 11d --	1/2 3/4 6/7 8/9 10/11 --	
K60	1b 2ab 3b 4a 7b 9b 10b 11a --	4c 5d 7d 10cd 11cd --	2/3 4/5 8/9	
K64	1b 2a 3a 7a 8b 9ab 11ab -- --	1c 3c 4d 7c 9c 11d	1/2 3/4 7/8 9/10 10/11 --	
KA1	1a 2b 7a 9a 11b --	1c 7c 10c 11c -- --	-- --	
--	-- --	-- --	-- --	
--	-- --	-- --	-- --	
--	-- --	-- --	-- --	
--	-- --	-- --	-- --	
--	-- --	-- --	-- --	
--	-- --	-- --	-- --	
--	-- --	-- --	-- --	
--	-- --	-- --	-- --	
--	-- --	-- --	-- --	

# 12 Circuits

## Keying codes

Code	P	K	V	CONFIGURATION
K27	2a 3b 5ab 8b 9b 10b 11b 12b --	1c 2d 5c 7c 8d 10d 11c -- --	1/2 3/4 5/6 7/8 9/10 11/12	
K42	3b 9b 10a 11a 12a --	3c 6cd 10d 11c -- --	1/2 3/4 7/8 9/10 11/12 --	
K48	1ab 3b 5b 6b 7b 8b 9a 11ab --	2d 3c 4d 5c 8d 9c 10d 11c --	1/2 3/4 5/6 7/8 9/10 11/12	
K59	1a 3ab 5b 6a 7b 8b 10b 11b 12b	1c 2d 4d 6d 7c 9c 10d 12d --	1/2 3/4 5/6 7/8 9/10 11/12	
K60	1ab 3b 4ab 5b 8ab 9a 10a 12ab --	1c 4d 5c 6d 7c 9c 11c -- --	1/2 3/4 5/6 7/8 9/10 11/12	
K61	1a 2a 4ab 5a 6b 8a 9ab 10b 11b 12b	1c 3c 5c 7c 8d 10d 11c -- --	1/2 3/4 5/6 7/8 9/10 11/12	
K62	1a 2a 3ab 6ab 8ab 10a 11b 12b --	1c 3c 5c 7c 9c 10d 11c -- --	1/2 3/4 5/6 7/8 9/10 11/12	
K65	2b 3ab 6a 7a 9ab 10a 11a 12b --	1c 2d 5d 6d 10d 12d	1/2 3/4 7/8 9/10 11/12 --	
KA1	1a 2b 6b 9a 12b --	4c 5c 6d 9c -- --	-- --	

TOLERANCE		 Young Yak Enterprise Co., Ltd.			
X.	--				
X.X	±0.25				
X.XX	±0.15				
X.XXX	±0.05	TITLE			
ANGULAR --		Keying Codes			
APPROVALS		VIEW	SCALE	PART NO.	REV.
DRAWN	YunTing 18-MAY-2018		F	A504x	A36
CHECKED	Nancy 18-MAY-2018	UNIT	SIZE	DWG NO.	SHEET
APPROVED	Scott 18-MAY-2018	MM	A4	A504x-Keying Codes	22 OF 22



Customer Drawing